

[December 08, 2022]

## CHEM-E7190 (Exam)

**Exercise 01 (70%).** Consider a perfectly stirred biological reactor in which the biomass concentration  $x_1(t)$  and the substrate concentration  $x_2(t)$  are the state variables, and the substrate concentration in the feed  $u_1(t)$  and the dilution rate  $u_2(t)$  (the reciprocal of the residence time) are the control variables. The system evolves in time according to the dynamic model

$$\dot{x}_1(t) = \underbrace{x_1(t) [\mu(x_2(t)) - u_2(t)]}_{f_1(x(t), u(t) | \theta_x)}; \quad (1a)$$

$$\dot{x}_2(t) = \underbrace{u_2(t) [u_1(t) - x_2(t)] - \frac{1}{2} \mu(x_2(t)) x_1(t)}_{f_1(x(t), u(t) | \theta_x)}, \quad (1b)$$

where  $\mu(x_2(t)) = \frac{\theta_{x,1}}{\theta_{x,2} + x_2(t)} x_2(t)$  is the Monod growth rate with parameters  $\theta_x$  taking the values  $\theta_{x,1} = 0.6 \text{h}^{-1}$  and  $\theta_{x,2} = 0.2 \text{g l}^{-1}$ . We assume that the biomass concentration is measured: Thus, we also have the output equation

$$y(t) = \underbrace{x_1(t)}_{g(x(t), u(t) | \theta_y)} \quad (2)$$

For certain values  $u^{\text{SS}} = (u_1^{\text{SS}}, u_2^{\text{SS}})$  of the controls, the bioreactor presents a stationary state  $x^{\text{SS}} = (x_1^{\text{SS}}, x_2^{\text{SS}})$ . Determine the linear state-space model

$$\dot{x}'(t) = Ax'(t) + Bu'(t), \quad (3a)$$

$$y'(t) = Cx'(t) + Du'(t); \quad (3b)$$

which approximates model (1) and (2) around the point  $P = (u^{\text{SS}}, x^{\text{SS}})$ .

Remembering that the perturbation variables are defined as  $x'(t) = x(t) - x^{\text{SS}}$ ,  $u'(t) = u(t) - u^{\text{SS}}$ , and  $y'(t) = y(t) - y^{\text{SS}}$ , show the detailed steps needed to determine the matrices  $A$ ,  $B$ ,  $C$ , and  $D$  and the expressions obtained for each of their elements. Assume that only the dilution rate is known,  $u_2^{\text{SS}} = 0.4 \text{h}^{-1}$ .

**Exercise 02 (30%).** Consider the following approximation of a process model

$$\dot{x}(t) = \begin{bmatrix} -2 & 0 & 0 \\ 2 & -4 & 0 \\ 1 & 0 & -1 \end{bmatrix} x(t) + \begin{bmatrix} 1 \\ 0 \\ 0 \end{bmatrix} u(t); \quad (4a)$$

$$y(t) = [0 \ 1 \ 0] x(t) + [0] u(t) \quad (4b)$$

- (10%) Determine the stability of the system based on (the eigenvalues of)  $A$ ;
- (10%) Determine the controllability of the system based on the controllability matrix  $\mathcal{C} = [B|AB|\dots|A^{N_x-1}B]$ ,  $N_x$  is the dimensionality of the state;
- (10%) Determine the system observability from the observability matrix  $\mathcal{O}$ .

---

This is an open-book examination. In addition to pencil/pen, eraser and other essential writing material, students are allowed to use own printed copies of the course material and own personal notes/scribbles.